

Date:	Message No:	Revision:
2016-03-02	066-1	B

Spare part Software Update P2-System_Europe

Scanreco P2 Main Cards serial number up from „393216“ got an implementation of new ID-code stack.

In order to introduce new ID-codes a firmware update (receiver) is required inflicting non-compatibility towards previous firmware.

Current firmware version is identifiable on receiver LED-display during start-up

The proper Firmware version is.

Danfoss PVG: P2_Scanreco_PVG32_V48_Europe

RSQ: P2_Scanreco_PWM_V47_Europe

The update is available thru PALDIAG 2016.00 or higher.

The same firmware can be used for P2A as P2B.

In tandem mode (crane, stabilizer) all included receiver must have firmware update.

Without this update, pairing isn't possible - learn mode will fail!

P2 Main card



P2 Receiver



Main Card

Palfinger Part no.	Part Description	Update Identification
EEA4915	P2 Main card Maxi Linear L1	Serial number ➤ 393215
EEA4916	P2 Main card Maxi Joystick	
EEA5470	P2 Main card Maxi Linear L2	
EEA4790	P2 Main card Mini Linear L1	
EEA5471	P2 Main card Mini Linear L2	
EEA4791	P2 Main card Mini Joystick	

Receiver Danfoss

Palfinger Part no.	Part Description	Update Identification
EEA4570	P2 Receiver Danfoss 433MHz	Firmware SW 4.8
EEA5709	P2B Receiver Danfoss 433MHz	
EEA5653	P2B Receiver Danfoss 429MHz	
EEA10519	P2B Receiver Danfoss	

Receiver PWM

Palfinger Part no.	Part Description	Update Identification
EEA4571	P2 Receiver PWM 433MHz	Firmware SW 4.7
EEA5654	P2B Receiver PWM 429MHz	